

EDSR400M Setup

- 1/ Plug Monitor into 6 pin Din connector or RCA MON socket.
- 2/ If in **REC** mode press **STOP**– MENU button should be selected if not then press MENU
- 3/ Enter setup as below using arrows on top row of buttons
- 4/ Then Press **NEXT** Page to advance to next screen selection etc.

NORMAL RECORD SETTING MENU (SCREEN 1)

SPEED:	: 10 IPS (allow 5 per cam)
QUALITY	:STANDARD
DISK FULL	: REWRITE
AUTORECORD	: ON (Ver.1.2.1N & 1.2.2.PS)
CAMERA1	: ON
CAMERA2	:OFF (ON for 2nd camera)
CAMERA3	:OFF (ON if 3rd camera)

Addition Notes

To play recording set AUTORECORD to **OFF**
When finished playing set AUTORECORD to back to **ON**.
(1.0.11 firmware does not have autorecord)

BUZZER MENU (SCREEN 3)

BUZZER	: ENABLE
RECORD IN	:OFF
ALARM IN	:OFF
MOTION IN	:OFF
DISK FULL	:OFF
VIDEO LOSS	: ON
TIMER	:OFF

Set BUZZER to ENABLE
If DVR buzzer is sounding then camera may not be connected ie video loss.

SYSTEM SETTING MENU (SCREEN 9)

PLAY WITH AUDIO	: ON
DISK RENEW	:NO Formats Hard Drive
SYSTEM UPDATE	:NO
LOAD DEFAULT	:NO
PASSWORD INABLE	:NO
PASSWORD	:123456
GPS OPERATION	:OFF

Set PLAY WITH AUDIO to ON
Set Yes if you need to format HDD

CLOCK/LANGUAGE MENU (SCREEN 10)

DATE	2013/11/20	WED
TIME	07:21:09	
MENU LANGUAGE:	ENGLISH	
VIDEO SYSTEM:	PAL	
VERSION:	<u>1.2.2.PS</u>	
RELEASE DATE:	2005/07/2013	

Set DATE, TIME, LANGUAGE.
Set VIDEO SYSTEM to PAL

Ensure VERSION is correct ie 1.2.2.PS
Using CF card update to 1.2.1.N first than reboot than load 1.2.2.PS. Note: file name is edsr400.exe

TITLE SETTING MENU (SCREEN 11)

DAYLIGHT SAVING SETTING (MENU 11)	
DAYLIGHT SAVING:	OFF
START TIME:	
FIRST SUN.....	

Ensure daylight saving is OFF

Finally press MENU button and REC light should come on.

HDD orange LED should start blinking and Drivers camera red led should be blinking at 1/sec.

Notes:

REC will not work unless a working cameras are connected and hard drive draw is locked.

Depot Reader: Ensure depot PC has version 2.3.2.2 software install for correct operation with Windows XP Pro with service pack 3. Windows 7 is not compatible.